

CX-TRK, CX-TRN, CX-TRP AND CX-TRX TRANSFORMERS/RECTIFIER












FEATURES

- AC AND DC MODELS
- STANDARD MOUNT AND PLUG-IN MODELS
- PLUG-IN MODELS ARE UL/CUL LISTED
- FUSED MODEL FOR ADDITIONAL CIRCUIT PROTECTION
- 3 YEAR WARRANTY

DESCRIPTION

Camden offers a range of 12VAC to 24VAC standard, plug-in and panel (nipple) mount transformers to support any low voltage system application.

The CX-5024 rectifier is used to convert AC power, for use with DC powered devices.

PANEL (NIPPLE) MOUNT		
 	CX-TRN-2024	24 VAC, 20 VA nipple mount transformer
STANDARD MOUNT		
 	CX-TRX-2012	12 VAC, 20 VA standard mount transformer
	CX-TRX-4024	24 VAC, 40 VA standard mount transformer
 	CX-TRX-5024	24 VAC, 50 VA standard mount transformer
FUSED, STANDARD MOUNT		
 	CX-TRX-2024	24 VAC, 20 VA, fused, standard mount transformer
	CX-TRK-2450	24 VAC, 20 VA, standard mount transformer and AC/DC rectifier
PLUG-IN		
 	CX-TRP-4016	16 VAC, 40 VA plug-in transformer
RECTIFIERS		
	CX-5024	Rectifier, (AC-DC) 50 VA

SPECIFICATIONS

VOLTAGE:	120V AC 60HZ
DIMENSIONS:	CX-TRN-2024: 2" L x 2 3/8" W x 2 1/4" H (51mm x 60mm x 57mm)
	CX-TRX-2012: 3" L x 2" W x 2 1/8" H (76mm x 51mm x 54mm)
	CX-TRX-4024: 2" L x 2 3/8" W x 2 1/2" H (51mm x 60mm x 64mm)
	CX-TRX-5024: 2 1/8" L x 3 1/8" W x 2 5/16" H (54mm x 80mm x 60mm)
	CX-TRX-2024: 2" L x 2 3/8" W x 2 1/2" H (51mm x 60mm x 64mm)
	CX-TRP-4016: 3 1/2" L x 2 1/2" W x 2 1/8" H (89mm x 64mm x 54mm)
	CX-5024: 1" L x 3/4" W x 1/4" H (25mm x 19mm x 6mm)