



ELECTRIFIED EXIT TRIM

Command Access ET25



- *Field Reversible*
- *12 or 24 VDC*
- *Low Current Draw*
- *3-Year Warranty*

The easier and more affordable solution

The Command Access electronic **ET25 exit trim** is perfect for stairwell conditions or applications where electric pullback of the exit device's latchbolt is cost prohibitive or not required. This is especially practical in applications where fire/life safety codes require "fail safe" condition which is not an option with electrified latch pullback devices. Because the current draw is quite low there is no need for a more expansive power supply to provide the surge current.

U.S. Customer Support
1-888-622-2377

Visit our website for more details
www.CommandAccess.com

Canada Customer Support
1-855-823-3002

Models Available

ET25EL - storeroom:
(fail safe)

Outside lever locked (EL) electronically. Switched power allows outside lever to retract latch(es). Outside key momentarily unlocks outside lever to retract latch(es). Inside push pad is always free for immediate egress.

ET25EU - storeroom:
(fail secure)

Outside lever unlocked (EU) electronically. Switched power allows outside lever to retract latch(es). Outside key momentarily unlocks outside lever to retract latch(es). Inside push pad is always free for immediate egress.

Lever Styles Available

L6

Finishes Available

626

FEATURES:

- Continuous duty solenoids used to insure trouble-free operation
- Internally mounted solenoid to ease installation (no special door prep required)
- No hassle 3-Year Warranty

OPTIONS:

- Available Fail Safe (Electrically Locked) or Fail Secure (Electrically Unlocked)
- Voltage options - 12V or 24V (AC/DC)
- REE - Request to Enter switch available
- CRU2 - Current Reduction Unit to improve solenoid life in "continuously on" applications
- CRU2i - The intelligent CRU2: automatically detects DC input voltage between 12 to 30 volts and converts it to operate our 12V exit trims. Additionally, it adjusts the current to the solenoid allowing the exit trim to run cooler and last longer without any manual adjustments.

SPECIFICATIONS:

- Operating Voltage - 12 or 24VAC/DC (+or- 10%) (must specify 12 or 24 volts when ordering)
- Amperage - 12V = 250 mA / 24V = 150 mA
- Solenoid coil resistance - 12V = 49 Ω / 24V = 159 Ω

Model No.	Notes:		
Customer:	Job No./Name:	Date:	Provided by: