



ALARM LOCK

345 Bayview Avenue, Amityville, New York, U.S.A. 11701
For Sales and Repairs 1-800-ALA-LOCK • For Technical Service 1-800-645-9440
Fax: 631-789-3383 • info@alarmlock.com

Note: Technical Service is for security professionals only

ALARM LOCK Tech Support

TECH TIP



Date: Wednesday, June 13, 2012

Subject: Enable Toggle Passage Mode for models without the Toggle Feature

Models: DL2800, DL3000

The "**Group 2 Codes Toggle Passage Mode**" feature is available for all but the two Trilogy T3 Models listed above. The following details the most efficient steps to enable the "Toggle Passage Mode" for lock models that do not have this "toggle code" feature. The first step is to create a 3-digit Manager or Supervisor code:

STEP 1: Place the lock into Program Mode: Press the current Master Code followed by the  button. Listen for the 6 beeps.

STEP 2: Program your new 3-digit Manager Code by pressing:

      [_ _ _] 
[User #] [New Manager Code]

STEP 3: Exit programming mode (press and hold any button for 5 seconds until a series of beeps are heard).

To **ENABLE PASSAGE MODE:**

Press [New Manager Code] followed by , pause for 6 beeps, press  
 , then press and hold any button for 5 seconds (to exit Program Mode).
The lock will now remain unlocked (called "Passage Mode") indefinitely.

To **DISABLE PASSAGE MODE:**

Press [New Manager Code] followed by , pause for 6 beeps, press  
 , then press and hold any button for 5 seconds (to exit Program Mode).
The lock will now remain locked indefinitely.

NOTE: If needed up to 5 different Manager and 5 different Supervisor codes may be programmed. Available Manager User Numbers are; 02, 03, 04, 05, 06. Available Supervisor User Numbers are; 07, 08, 09, 10, 11. Both the Manager and Supervisor Codes have the ability to enter Program Mode. The Supervisor Codes have fewer programming options (see the Programming Instructions for more information).