

## 3000 Series 1500 Lb.



3000

Electromagnetic locks, surface mounted for outswing or inswing single or double doors.  
 Size: 1-1/2"D x 2-3/4"H x 11"L Single or 22"L Double  
 Multi-voltage auto-sensing 12/24 VAC/VDC  
 Current Draw: 374 mA @ 12VDC Single / 748 mA Double  
 210 mA @ 24VDC Single / 420 mA Double  
 Adjustable Relock Time Delay (Former TD Option) is standard on all models.



3001

MODEL	PRODUCT	FINISH	WEIGHT
<b>3000</b>	Single Electromagnetic Lock Outswing	US28	10 Lbs.
<b>3001</b>	Single Electromagnetic Lock Pair Outswing	US28	10 Lbs.
<b>3002</b>	Double Electromagnetic Lock Outswing	US28	20 Lbs.
<b>3000TJ30</b>	Single Electromagnetic Lock Inswing	US28	13 Lbs.
<b>3002TJ32</b>	Double Electromagnetic Lock Pair Inswing	US28	26 Lbs.



3002

### OPTIONS

- **DSM** Door Status Switch - Signals door closed or ajar.
- **DSM2** Door Status Switch - For the 3002 Series.
- **HSM** High Security Monitor. Includes the following:  
 Door Status Switch - Signals door closed or ajar.  
 Dynastat Force Sensor - Indicates efficient magnetic bond.
- **HSM2** High Security Monitor - For the 3002 Series.
- **VOP** Value Option Package. Includes the following:  
 Door Status Switch - Indicates door closed or ajar.  
 Dynastat Force Sensor - Indicates efficient magnetic bond.  
 Anti-Tamper Switch - Signals removal of wiring access cover.
- **VOP2** Value Option Package - For the 3002 Series.
- **CLH** Custom Length Housing - See page 24.
- **\* LCB** Basic Lock Less Circuit Board
- **LED** Bi-Color LED - For local signaling of lock status.  
 (Requires HSM or VOP Option. Not available on TJ models.)
- **LED2** Bi-Color LED's (2) - For the 3002 Series. (Requires HSM2 or VOP2 Option. Not available on TJ models.)
- **# LP** Low Power Coil - 12V only @ 0.16 Amps (Single Lock)
- **LP2** Low Power Coils - 12V only @ 0.32 Amps (Double Lock)
- **OFA** Offset Armature - For narrow style storefront doors.  
 (When ordered with lock)
- **SF** Special Finish - Standard finish US28. Special anodized finishes see page 56.



NYC MEA  
#23-92-E

CSFM

Notes: • DSM, HSM, VOP and LED options not available on the 3001 Series.  
 \* DSM, HSM, VOP and LED options not available with the LCB option.  
 # LP option may not be combined with HSM or VOP options.