

ET26 Series



The easier and more affordable solution

The Command Access ET26 exit trim is perfect for stairwell conditions or applications. The ET26 work with the Command Access PD25 RIM/SVR exit devices, Cal Royal 7700 RIM/SVR exit devices, & Von Duprin 98/99 RIM/SVR/CVR exit devices. The ET25 is the electrified version.

LEVER TRIM:



• L6



• L7*



• L17

FINISHES:

• 613 *

• 625 *

• 626

**Please call to confirm availability*

U.S. Customer Support
1-888-622-2377

Visit our website for more details
www.CommandAccess.com

Canada Customer Support
1-855-823-3002

Models Available

COMPLETE TRIM FOR COMMAND ACCESS PD25

Schlage C compatible cylinder included. Retrofits Cal-Royal 7700 series. R/SVR version retrofits Von Duprin 98/99 RIM/CVR/SVR. Handing Field reversible, rigid lever.

FUNCTION	ENTRANCE	STOREROOM	PASSAGE	NIGHT LATCH	DUMMY	↺	↻	↻	↺	626	613	625	S	L/F/C	REE	
LEVER TRIM	ET26 ELT	ET26 SLT	ET26 PLT	-	ET26 DLT									✓	✓	✓ ²
THUMBPIECE TRIM	ET26 ETT	ET26 STT	ET26 PTT	-	ET26 DTT	FOR COMPLETE EXIT TRIM ONLY							✓	✓	-	
PULL TRIM	-	-	-	ET26 NPT ¹	ET26 DPT									✓	-	-
COMPLETE TRIM includes In-stock Trim						-	L6	L7*	L17*	✓	+20	-	✓	-		\$60

1- Only works on RIM devices 2. Only available on entrance function
 *Limited Availability

SPECIFICATIONS:

- Rigid, non-clutch mechanism.
- Double heavy duty spring support to prevent sagging and enhance operation.
- Grade 1, thru-bolted design. Non-handed design. Easily field reversible.
- Hardened steel heavy duty tailpiece. Available for fire and non-fire rated rim and vertical rod exit devices.
- Lever Trim: 2-3/4" width x 10 1/4" length. Lever length: 4 3/4". Fits and covers 2 1/8" 161 cutout.
- TP & Pull Trim: 2-5/8" width x 14 1/2" length.
- Standard 1 3/4". For 2 1/4" thick doors order additional part #tail3
- Lever & Thumb piece trim Standard mortise cylinder. High security cylinders accepted ie. Medco, Assa, and Kaba.
- Pull trim Rim Cylinder standard

FEATURES:

- Retrofits Cal Royal 7700 series & Von Duprin 98/99
- No hassle 3-Year Warranty

OPTIONS:

- REE - Request to Enter switch available. Lever trim only.

Model No.	Notes:		
Customer:	Job No./Name:	Date:	Provided by: