





# inPulse+

Multi-Biometric Finger Vein & Fingerprint Access Control Reader

**inPulse+** is a multi-biometric reader capable of capturing and processing BOTH finger vein pattern & fingerprint biometric data at the same time.



### Biometric Performance:

Combines revolutionary SilkID fingerprint sensor and powerful finger vein pattern sensor to achieve the highest degree of accuracy. Identifies users in less than 2 seconds.



### Communication:

Weigand output for when connecting to an access control panel and Ethernet port for fast and reliable network communication.



### Capacity:

Stores up to 1,000 finger vein and 1,000 fingerprint templates. Data can be backed up to a USB flash drive and transferred to another inPulse+ in the absence of network connectivity.



### Options:

Internal Proximity Card or Mifare Card reader allows dual factor authentication for access control.



### Easy Operation and Management:

Works without a computer. Complete setup and programming can be done via the "inPulse+keypad and embeded firmware. Audio-Visual indication for acceptance and rejection of valid/invalid fingerprints, cards and passwords.



### Access control:

Relay Outputs for electric lock and alarm. Inputs for door status sensor and request to exit hardware. Supports multiple time zones and personnel groups for programming valid entry zones.




### For Software Developers:


Free SDK and development tools are available for developers/partners who wish to integrate inPulse+ with any application which requires verifying people. Custom development is also available for OEM partners upon request.

# Configuration

# Wiegand Output Input Input Door Sensor Exit Button Door Bell Button

## **Dimensions**





# Specifications

### Capacity

Finger Veins: 1,500 Fingerprints: 1,500 Cards: 2,000

### **Access Control Interface**

Lock Relay Output Alarm Output/Auxiliary Input Exit Button/Door Sensor Doorbell Output

### Communication

TCP/IP USB Host Wiegand Input/Output

### Hardware

ZK Fingerprint Sensor 2.8 Inch TFT-LCD Touch Screen 125 kHz ZKAccess Card Reader Tamper Switch Alarm

### **Standard Functions**

Access Levels/Groups/Holidays DST/Bell Schedule Duress Mode (Password) Anti-Passback Record Query Custom Wallpaper & Screen Saver

### Software Compatibility ZKBioSecurity

### Additional Info

Working Temperature: 14° F to 122° F (-10° C to 50° C) Dimensions: 8 x 3.3 x 4 inches Package Includes: 12V 3A Power Supply

### Power

Operating Voltage 12V DC Current Draw < 500mA

# Part Numbers

### inPulse+

includes ZKAccess card reader

### inPulse+ HID

includes HID 125 kHz card reader


### inPulse+ Mifare

includes Mifare card reader

### inPulse+ iClass

includes HID iClass card reader


# What's in the Box



inPulse+



Installation Template



Back Plate



Measuring Tape



Network Cable



Screws



AC Power Adapter



Screwdriver



Cables



### **ZKTeco USA**

6 Kingsbridge Road, Unit 8, Fairfield, NJ 07004

Phone: (862) 505-2101 • Fax: (862) 204-5906 • sales@zkaccess.com • www.zkaccess.com

