








PTE-1

REX (Request to Exit) switch

Description

The new PTE-1 exit switch connects to any 12V access controller and provides users FAST SIMPLE door egress. It's small, lightweight, IP68-waterproof and has a simple Red/Green LED so users can see it's status. PTE-1 is included in ZKAccess door kits and can be purchased separately, as well.

Wiring Diagram

-  Red — + 12V DC
-  Black — —
-  Yellow — NC
-  White — COM
-  Green — NO

Specification

Dimensions: 114L x 70W x 16H(mm)

Voltage: 12-24V

Current: Standby 30mA

Operation: 70mA

Output Contact: NO/NC/COM

Current Rating: 1A @ 30VDC 0.5A @ 125VDC

Waterproof Level: IP-68

LED Status: Red: Standby, Green: Operation

Wire Color: Red: Positive, Black: Negative
Yellow: NC, White: COM, Green: NO

ZKTeco USA

6 Kingsbridge Road, Unit 8, Fairfield, NJ 07004
Phone: (862) 505-2101 • Fax: (862) 204-5906 • sales@zkaccess.com • www.zkaccess.com